

Stabilization of Uncertain Descriptor Bilinear Dynamical System Using Logarithmic Norm

Ghazwa Faisal Abd, Radhi Ali Zaboon

Department of mathematics, college of science/ Al-Mustansiriya University, Baghdad, Iraq

Abstract: This paper shows the importance of Logarithmic norm in studying stability of linear/nonlinear descriptor systems with parametric uncertainty. Some basic definitions and theorems about Logarithmic norm and the Dini derivative, have been given. Stabilization of uncertain bilinear descriptor systems via logarithmic norm approach has been proposed and proved with illustrations.

Index Terms: Bilinear systems, Descriptor system, Logarithmic Norm, Uncertain System.

I. INTRODUCTION

Bilinear systems are important sub classes of nonlinear systems with many applications in engineering, biology and economics. The control of bilinear systems has been extensively studied in the 70s and at the beginning of the 80s of the last century and remarkable by [7]. In [2] Germund Dahlquist introduced the logarithmic norm in order to derive error bound in initial value problem using differential inequalities that distinguished between forward and reverse time integration. Logarithmic norm plays an important role in the stability analysis of a continuous dynamical system see [12], [13]. Both [2],[5] provide tables for how to compute logarithm for some common norms as well as numerous basic properties of the logarithmic norm.

II. DESCRIPTION OF THE PROBLEM

Consider the descriptor bilinear system

$$x_1' = (A + \delta A)x_1(t) + (B + \delta B)u(x_1(t))x_1(t) \dots (1a)$$

$$0 = (C + \delta C)x_1(t) + (D + \delta D)x_2(t) \dots (1b)$$

Where $x_1(t) \in \mathbb{R}^p$, $x_2(t) \in \mathbb{R}^{n-p}$, $A \in \mathbb{R}^{p \times p}$, $B \in \mathbb{R}^{p \times 1}$, $C \in \mathbb{R}^{(n-p) \times p}$, $D \in \mathbb{R}^{(n-p) \times (n-p)}$ and δA , δB ,

δC , δD are constant perturbations matrices with

$$\|\delta A\| \leq a, \|\delta B\| \leq b, \|\delta C\| \leq c, \|\delta D\| \leq d \text{ and } a, b, c,$$

d are positive integers. With a nonlinear control $u(x_1(t))$,

the solution of “(1)” exists for so-called consistent initial value x_0 of $x(t)$. The set of the consistent initial values of (1) are denoted by W_k .

One can define manifold $M_k \subseteq \mathbb{R}$ determined by “(1b)” as

$$M_k = \mathcal{N}((C + \delta C \quad D + \delta D)).$$

For the system governed by “(1)”, the set W_k of the consistent initial values is equal to the manifold M_k that means $W_k = M_k$ in other words, a consistent initial value x_0 has satisfy

$$0 = (C + \delta C)x_{10} + (D + \delta D)x_{20}$$

that equivalent to

$$x_0 \in W_k = M_k = \mathcal{N}((C + \delta C \quad D + \delta D)).$$

III. BASIC CONCEPT

In this section, a survey over different concepts and methods that one can find it in [1-10]

A. Definition

Let f be a function defined on $I = [a, b]$.

Then

$$D^+ f(x) = \limsup_{h \rightarrow 0^+} \frac{f(x+h) - f(x)}{h}$$

$$D_+ f(x) = \liminf_{h \rightarrow 0^+} \frac{f(x+h) - f(x)}{h}$$

Be right upper and lower Dini derivative respectively.

B. Remark

The properties of the Dini derivative can be found in [3],[11].

C. Definition

The Logarithmic norm is a real valued functional on operators and is derived from either an inner product or vector norm or its induced operator norm.

D. Definition

Let A be square matrix and $\|\cdot\|$ be an induced matrix norm then associated logarithmic norm μ of A is defined

$$\mu(A) = \limsup_{h \rightarrow 0^+} \frac{\|I + hA\| - 1}{h}$$

Where I is identity matrix of the same dimension of A , h is real, positive number.

E. Remark

One can find the properties of the logarithmic norm in [3].

F. Lemma

(Generalization of Gromwell's lemma)

Let $a, b, n, k \in \mathbb{R}$, $a < b$, $n > 1$ and $K > 0$,

$f: [a, b] \rightarrow \mathbb{R}^+$ an integral function such that

$$\forall a, \beta \in [a, b] (\alpha < \beta): \int_\alpha^\beta f(s) ds > 0 \text{ and}$$

$$x: [a, b] \rightarrow \mathbb{R}^+ \text{ if}$$

$$x(t) \leq K + \int_0^t f(s) [x(s)]^n ds \text{ and}$$

$$1 - (n-1)K^{n-1} \int_\alpha^t f(s) ds > 0, \text{ then}$$

$$x(t) \leq \frac{K}{\left[1 - (n-1)K^{n-1} \int_\alpha^t f(s) ds\right]^{\frac{1}{n-1}}}$$

IV. STABILIZATION OF UN CERTAIN DESCRIPTOR BILINEAR DYNAMICAL SYSTEM USING LOGARITHMIC NORM

A. Theorem

Consider the descriptor bilinear control system “(1a)”, “(1b)” with

1- δA is chosen to be a constant perturbation such that

$$e^{\mu[A+\delta A]t} \leq \gamma e^{-\alpha t} \quad \forall t \geq 0, \alpha, \gamma \text{ are positive integers}$$

2- The sub matrix D with $|D| \neq 0$ and

$$\|D^{-1}\delta D\| < 1$$

3- A nonlinear control $u(x_1(t))$ given by

$$u(x_1(t)) = \frac{r(x_1(t))}{\|x_1(0)\|^2}, \forall x_1(t) \in W_k \text{ such that } x_1(0) \neq 0$$

$r(x_1(t))$ is a vector function satisfy

$$\|r(x_1(t))\| \leq f(t) \|x_1(t)\|^2$$

Where

$$f: \mathbb{R}^+ \rightarrow \mathbb{R}^+ \text{ and } \alpha, \gamma \text{ positive integer such that } \forall t \geq 0$$

$$1 - 2\gamma^2(\|B\| + b) \int_0^t e^{-2\alpha s} \|f(s)\| ds$$

is positive and bounded.

Then the system “(1)” is asymptotically stable

Proof:

Let $x(0) = [x_1(0) \ x_2(0)]^T$ and the space of consistent initial condition (W_k) can be obtained by substitute the condition (3) in to equation “(1b)”

$$W_k = \{(x_1, x_2) | x_2(0) = -\frac{(C+\delta C)}{(D+\delta D)} x_1(0) \text{ that's mean}$$

$$x(0) \in \mathcal{N}([C + \delta C D + \delta D]) \text{ with } D + \delta D \neq 0 \quad \text{and}$$

$$x_1(0) \neq 0\}$$

From “(1a)”

$$x_1' = (A + \delta A)x_1(t) + (B + \delta B)u(x_1(t))x_1(t)$$

Using Dini derivative

$$D_t^+ \|x_1(t)\| \leq \limsup_{h \rightarrow 0^+} \frac{\|x_1(t+h)\| - \|x_1(t)\|}{h}$$

$$= \lim_{h \rightarrow 0^+} \frac{\|x_1(t) + hx_1'(t)\| - \|x_1(t)\|}{h}$$

$$\leq \lim_{h \rightarrow 0^+} \frac{\|x_1(t) + h(A + \delta A)x_1(t)\| - \|x_1(t)\|}{h} + \|(B + \delta B)(u(x_1(t))x_1(t))\|$$

$$\leq \lim_{h \rightarrow 0^+} \frac{\|I + h(A + \delta A)\| - 1}{h} \|x_1(t)\| + \|(B + \delta B)(u(x_1(t))x_1(t))\|$$

$$= \mu[A + \delta A] \|x_1(t)\| + \|(B + \delta B)(u(x_1(t))x_1(t))\|$$

Where

$$\mu[A + \delta A] = \lim_{h \rightarrow 0^+} \frac{\|I + h(A + \delta A)\| - 1}{h} \triangleq \bar{\mu}$$

Now

$$D_t^+ \|x_1(t)\| \leq \bar{\mu} \|x_1(t)\| + \|(B + \delta B)(u(x_1(t))x_1(t))\|$$

Multiply both sides of the resulting inequality by $e^{-\bar{\mu}t}$

to get

$$D_t^+ \{ \|x_1(t)\| e^{-\bar{\mu}t} - \bar{\mu} e^{-\bar{\mu}t} \|x_1(t)\| \} \leq \|(B + \delta B)u(x_1(t))x_1(t)\| e^{-\bar{\mu}t} \dots (2)$$

And by integrating both sides of (2) one can get

$$\|x_1(t)\| e^{-\bar{\mu}t} - \|x_1(0)\| \leq \int_0^t \|(B + \delta B)u(x_1(s))x_1(s)\| e^{-\bar{\mu}s} ds \dots (3)$$

Substitute $u(x_1(t))$ in (3) to get

$$\|x_1(t)\| \leq e^{\bar{\mu}t} \|x_1(0)\| +$$

$$\int_0^t e^{\bar{\mu}(t-s)} \|B + \delta B\| \frac{\|f(s)\| \|x_1(s)\|^2}{\|x_1(0)\|^2} \|x_1(s)\| ds.$$

$$\|x_1(t)\| \leq e^{\bar{\mu}t} \|x_1(0)\|$$

$$\left\{ 1 + \int_0^t e^{-\bar{\mu}s} \|B + \delta B\| \|f(s)\| \|x_1(s)\|^3 \|x_1(0)\|^{-3} ds \right\} \dots (4)$$

Now divide both sides of (4) by $e^{\bar{\mu}t} \|x_1(0)\|$

$$\frac{\|x_1(t)\|}{e^{\bar{\mu}t} \|x_1(0)\|} \leq 1 + \int_0^t e^{-\bar{\mu}s} \|B + \delta B\| \|f(s)\| \left[\frac{\|x_1(s)\|}{e^{\bar{\mu}s} \|x_1(0)\|} \right]^3 ds$$

Since δA and $f(t)$ be chosen such that condition (1), (3) satisfied and applying lemma (3.6)

$$\frac{\|x_1(t)\|}{e^{\bar{\mu}t} \|x_1(0)\|} \leq \frac{1}{\sqrt{1 - 2\gamma^2(\|B\| + b) \int_0^t e^{-2\alpha s} \|f(s)\| ds}}$$

$$\|x_1(t)\| \leq \frac{\gamma e^{-\alpha t} \|x_1(0)\|}{\sqrt{1 - 2\gamma^2(\|B\| + b) \int_0^t e^{-2\alpha s} \|f(s)\| ds}}$$

$$\text{Hence } \lim_{t \rightarrow \infty} \|x_1(t)\| \rightarrow 0$$

And

$$\|u(t)\| \leq f(t) \frac{\gamma^2 e^{-2\alpha t}}{1 - 2\gamma^2(\|B\| + b) \int_0^t e^{-2\alpha s} \|r(s)\| ds}$$

Now for “(1 b)”

Since $\|D^{-1}\delta D\| < 1$ and $D + \delta D = D(I + D^{-1}\delta D)$

Then

$$x_2(t) = -D^{-1}(I + D^{-1}\delta D)^{-1}(C + \delta C)x_1(t)$$

$$\lim_{t \rightarrow \infty} \|x_2(t)\| \leq \frac{\|D^{-1}\|}{1 - \|D^{-1}\delta D\|} (\|C\| + c) \lim_{t \rightarrow \infty} \|x_1(t)\| \rightarrow 0$$

B. Example

For the uncertain bilinear descriptor system “(1a)”, “(1b)” assume that

$$A = \begin{pmatrix} 0 & 0 \\ 0.5 & 0 \end{pmatrix}, \quad B = \begin{pmatrix} -1 & 0 \\ 0 & 0 \end{pmatrix}, \quad C = \begin{pmatrix} -1 & 0 \\ 0 & 1 \end{pmatrix} \quad \text{and}$$

$$D = \begin{pmatrix} 0 & 1 \\ -1 & 1 \end{pmatrix}.$$

$$\delta A = \begin{pmatrix} -0.3 & 0 \\ -0.7 & -0.2 \end{pmatrix}, \quad \delta B = \begin{pmatrix} 0.2 & 0 \\ 0 & 0 \end{pmatrix}, \quad \delta C = \begin{pmatrix} 0.2 & 0 \\ 0 & 0 \end{pmatrix}$$

$$\text{and } \delta D = \begin{pmatrix} 0 & 0 \\ 0.3 & 0 \end{pmatrix}.$$

Step (1): $\|\delta A\| \leq 1, \|\delta B\| \leq 1, \|\delta C\| \leq 1, \|\delta D\| \leq 1$

Step (2): Set $f(t) = \sin(t)$,

$$\|u(x_1(t))\| \leq \frac{\sin(t) \|x_1(t)\|^2}{\|x_1(0)\|^2}$$

Step (3): To find the consistent initial condition space where

$$x(0) \in W_k = \mathcal{N}([C + \delta C \ D + \delta D])$$

$$W_k = \{(x_{10}, x_{20}, x_{30}, x_{40}) | (x_{10}, x_{20}, x_{30}, x_{40}) = (a_1, -0.8a_1 - 0.7a_2, a_2, 0.8a_1)\}$$

Set $a_1 = 0, a_2 = 1$ one can get $(0, -0.7, 1, 0)$

Step (4): $D^{-1}\delta D = \begin{bmatrix} -0.3 & 0 \\ 0 & 0 \end{bmatrix}$ then $\|D^{-1}\delta D\| < 1$

Step (5): For $\gamma = 1, \alpha = 2$

$$1 - 2(1 + 1) \int_0^t e^{-4s} \| \sin(s) \| ds$$

$$= 1 - 4(-1/5 e^{-2s} \cos(s) - 2/5 e^{-2s} \sin(s)) \Big|_0^t,$$

is positive and bounded

Step (6): Using Dini derivative to find logarithmic norm as

$$\mu[A + \delta A] = \lim_{h \rightarrow 0^+} \frac{\|I + \begin{bmatrix} -0.3 & 0 \\ -0.2 & -0.2 \end{bmatrix} h\| - 1}{h} = \bar{\mu}$$

Step (7): Using theorem (4.1) one can find

$$\|x_1(t)\| \leq \frac{\gamma e^{-\alpha t} \|x_1(0)\|}{\sqrt{1 - 2\gamma^2(\|B\| + 1) \int_0^t e^{-2\alpha s} \| \sin(s) \| ds}}$$

One can get $\|x_1(t)\| \leq \frac{0.7 e^{-2t}}{\sqrt{1 - 2(1+1) \int_0^t e^{-4s} \| \sin(s) \| ds}}$

$$\lim_{t \rightarrow \infty} \|x_1(t)\| \rightarrow 0.$$

Step (8):

$$x_2(t) = -D^{-1}(I + D^{-1}\delta D)^{-1}(C + \delta c)x_1(t)$$

$$= -\begin{bmatrix} 1 & -1 \\ 1 & 0 \end{bmatrix} \begin{bmatrix} 1.4286 & 0 \\ 0 & 1 \end{bmatrix} \begin{bmatrix} -0.8 & 0 \\ 0 & 1 \end{bmatrix} x_1(t)$$

$$= \begin{bmatrix} 1.2286 & -1 \\ -1.4286 & 0 \end{bmatrix} x_1(t)$$

$$\Rightarrow \lim_{t \rightarrow \infty} \|x_2(t)\| \leq \begin{bmatrix} 1.2286 & -1 \\ -1.4286 & 0 \end{bmatrix} \lim_{t \rightarrow \infty} \|x_1(t)\| \rightarrow 0$$

Then the system "(1)" is asymptotically stable.

V. CONCLUSION

The aim is to develop the modern formulism of the logarithmic norm and use it to stabilizing the bilinear uncertain system and give a simple example to illustrate the method.

REFERENCES

- [1] N.E. Alami, "Stabilization of Bilinear Systems by Linear and Nonlinear Feedback", Proc. of the Second International of Differential Equations, Marrakech, Marco.) 1995).
- [2] G. Dahlquist, "Stability and Error Bounds in the Numerical Integration of Ordinary Differential Equation", Uppsala, Stockholm, (1958).
- [3] O.P. Ferreira, "Dini Derivative and A Characterization for Lipchitz and Convex functions on Riemannian Manifolds", Non-linear Analysis, 68(2008), pp.1517-1528.
- [4] G. Giorgi and S. Komlosi, "Dini Derivatives in Optimization ", Springer, Vol.15, Iss.1, pp.3-30, (1992).
- [5] S. Gustaf, "The Logarithmic Norm History and Modern Theory", BIT Numerical Mathematics, 46(2006), pp.631-651.
- [6] S. Gustaf and H. Inmaculada, "Logarithmic Norms and Nonlinear DAE Stability", BIT, Numerical Math., Vol.42, No.4, pp.823-841, (2002).

- [7] R.R. Molher, "Bilinear Control Process", Academic Press, New York (1973).
- [8] M.R. Rama, "Ordinary Differential Equation": Theory and Application. Affiliated East-West Private Limited, (1980).
- [9] W. Renate, "On Logarithmic Norms for Differential-Algebraic Equations", Institute for Mathematic, Humboldt, Berlin, Iss.0863, Nno.40, pp.1-27, (2007).
- [10] T. Storm, "On Logarithmic Norms", SIAMJ.Num.An.Vol.12, No.5, (1975).
- [11] R. Wrede and M.R. Spiegel, "Advance Calculus", McGraw-Hill, New York, (2010).
- [12] S. Xueli, J.Peng, "A novel Approach to Exponential Stability of Nonlinear Systems with Time-Varying Delays", Journal of Computational and Applied Mathematics, 235(2011), pp.1700-1705.
- [13] A. Wan, "A New Approach to Exponential Stability Analysis of Nonlinear Systems", J.Appl. Math and Computing 19(2005), pp.345-351.
- [14] Q. Zhang, "Generalized Dahlquist Constant with Applications in Synchronization Analysis of Typical Neural Networks via General Intermittent Control", Advances in Artificial Neural Systems, Vol.2011, and Article Id: 249136, (2011).

AUTHOR'S PROFILE

Ghazwa Faisal Abd, Mathematics Dept./ College of Science/ Al-Mustansiriya University/ Baghdad/Iraq.

Radhi Ali ZAboon, Mathematics Dept. / College of Science/ Al-Mustansiriya University/ Baghdad/Iraq.